



SB903

Rechargeable Battery

The Shure rechargeable li-ion battery, SB903, user guide.
Version: 2 (2020-G)

Table of Contents

SB903 Rechargeable Battery	3	WARNING	3
Rechargeable Battery	3	Storing Batteries	3
Inserting the Battery into the Charger	3	Specifications	3
		Certifications	4

SB903 Rechargeable Battery

Rechargeable Battery

The SB903 lithium-ion rechargeable battery powers the SLX-D transmitters. Use the SBC10-903 single bay or SBC203 dual bay chargers to recharge SB903 batteries.

Always fully charge a new battery before first use. To fully charge a new SB903 battery, it must be placed directly in the charger. After the first charge, the battery can be charged by docking the transmitter in the SBC203 dual-bay charging station.

Inserting the Battery into the Charger

Place the battery into the charger, slotted side down.

WARNING

- Battery packs may explode or release toxic materials. Risk of fire or burns. Do not open, crush, modify, disassemble, heat above 140°F (60°C), or incinerate.
- Follow instructions from manufacturer
- Only use Shure charger to recharge Shure rechargeable batteries
- **WARNING:** Danger of explosion if battery incorrectly replaced. Replace only with same or equivalent type.
- Never put batteries in mouth. If swallowed, contact your physician or local poison control center
- Do not short circuit; may cause burns or catch fire
- Do not charge or use battery packs other than Shure rechargeable batteries
- Dispose of battery packs properly. Check with local vendor for proper disposal of used battery packs.
- Batteries (battery pack or batteries installed) shall not be exposed to excessive heat such as sunshine, fire or the like
- Do not immerse the battery in liquid such as water, beverages, or other fluids.
- Do not attach or insert battery with polarity reversed.
- Keep away from small children.
- Do not use abnormal batteries.
- Pack the battery securely for transport.

Storing Batteries

Store batteries in the charger when not in use. If batteries are to be stored for more than eight days, they should be removed from the charger and placed into a temperature controlled storage area. Recommended battery storage temperature is 10°C (50°F) to 25°C (77°F).

Specifications

SB903

Charge Voltage

4.2 V (± 0.03 V)

Charge Current

SBC10-903	220 mA
SBC203	625 mA (normal), 250 mA (reduced)

Nominal Voltage

3.6 V

Nominal Capacity

1200 mAh

Housing

Molded Polycarbonate

Charging Temperature Range

SBC10-903	10 °C to 45 °C (50 °F to 113 °F)
SBC203	0 °C to 10 °C (32 °F to 50 °F), reduced, and 10 °C to 45 °C (50 °F to 113 °F), normal

Dimensions

14.5 x 32.5 x 55.5 mm (0.57 x 1.28 x 2.19 in.), H x W x D

Weight

28 g

Certifications

This product meets the Essential Requirements of all relevant European directives and is eligible for CE marking.

- EMC Directive 2014/30/EU
- Battery Directive 2013/56/EU